

# CMS-200


## ACTi 1600 Channel 1-Bay Rackmount Standalone CMS




- Manage 1600 channels across multiple NVRs
- 100 licenses bundled
- Live view local up to 16 channels
- Synchronized playback:
  - Local up to 9 channels / 64 channels remotely
- Export video with RAW and AVI formats
- Event trigger, response and notification
- Mobile Client, Web Client, Workstation
- Location-based management with eMap
- TV Wall support by additional software license

### PHOTO INDICATION


### DIMENSION DIAGRAM



- |                  |                  |
|------------------|------------------|
| 1 Power Switch   | 7 LAN 2          |
| 2 Power LED      | 8 Line-Out Port  |
| 3 AC Power Input | 9 Display Port   |
| 4 DVI-D Port     | 10 USB 2.0 Ports |
| 5 VGA Port       | 11 USB 3.0 Ports |
| 6 LAN 1          | 12 Mic-In Port   |



### SOLUTION ARCHITECTURE



## PRODUCT SPECIFICATION

## CMS-200

## • General

|                           |   |
|---------------------------|---|
| Maximum Number of NVR     | Unlimited                                 |
| Maximum Number of Clients | 1 local, 5 remote (concurrent)            |
| Maximum Number of Cameras | 1600                                      |
| Free License              | 100 channels for video devices            |
| Compression               | H.264, MPEG-4, MJPEG                      |
| NVR Management            | Import management settings of NVR servers |

## • Live View

|                             |  |
|-----------------------------|--|
| Display Layout Mode         | 1, 4, 5, 6, 8, 9, 10, 12, 16, Custom   |
| View Manager                | An interface to define display layouts and the pre-set cameras within layout in the public or private view   |
| View Patrol                 | Automatic switch between different views or devices  |
| View Panel                  | Contains the list of pre-defined views for quick launch  |
| Instant playback            | Instant playback in live view window   |
| Layout Manager              | An interface to define display layouts and the pre-set cameras within layouts; full-screen mode available  |
| Device Panel                | Drag and drop video source from device panel into display layout   |
| Digital Zoom                | Zoom in/out digitally by mouse scroll wheel  |
| Manual Recording / Snapshot | Instant recording to NVR 3.0 Server upon mouse click / Instant snapshot upon mouse click   |
| Event Display Panel         | Alarm; Connection loss/recovery between server and client; the allocated disk space full; Point-of-sale (POS), access control and network I/O status |
| Two-Way Audio               | Audio sound from and to all the audio supported devices; audio broadcast to multiple devices at the same time  |
| Dual Stream Management      | Live view of stream 1 or stream 2 of dual stream devices   |

## • e-Map

|          |   |
|----------|---|
| Layout   | Area maps with camera icons, small live view windows; view linker; source linker; event trigger   |
| Setup    | E-Map image upload; camera positioning; vision angle and pointed direction of camera; view positioning; source positioning; extended devices for Point-of-sale (POS), Access Control, Network I/O, Car Park |
| PTZ Mode | Mouse PTZ mode to control e-Map video streams   |

## • PTZ

|                         |  |
|-------------------------|--|
| Control                 | Pan, tilt and zoom controls; speed control; both buttons and overlay controls                    |
| Preset Points and Tours | Activate NVR preset points or auto tours between preset points                                   |
| Joystick                | USB based joystick supported   |
| Default Protocol        | Auto-detect camera's PTZ protocol. Available protocols: ACTI, Pelco-P, Pelco-D, Dynacolor, Visca |

## • Storage

|                      |  |
|----------------------|--|
| HDD Interface        | Serial ATA                                 |
| Maximum HDD Capacity | 6TB x 1                                    |
| HDD Bay              | Maximum 1 SATA disk (Without Storage Disk) |

## • Search &amp; Playback

|                       |  |
|-----------------------|--|
| Recording Search      | Search video recordings by time, event, channel and bookmark from multiple NVRs, and listed as clickable thumbnails for full-size view and snapshot download |
| Playback Control      | Continuous forward and backward playback with speeds 1x/2x/4x/8x or frame-by-frame; pause; stop  |
| Synchronized Playback | 9 channels (local), 64 channels (remote)   |
| Manual Snapshot       | Instant snapshot from playback upon mouse click  |
| Digital Zoom          | Zoom in/out digitally by mouse scroll wheel or by zoom control buttons   |
| Video Export          | Export video clips in AVI or RAW format; text overlay and point-of-sale (POS) transaction data supported   |

## • Event Management

|                |   |
|----------------|---|
| Event Source   | Receive events from multiple NVR servers  |
| Event Trigger  | <b>NVR:</b> source loss and recovery; schedule service start and stop; disk status; bookmark; GPS positioning/reception Loss<br><b>Device:</b> video motion detection; passive IR sensor; external device through digital input; video loss and recovery; network loss and recovery; point-of-sale (POS) status; network I/O status; access control allowed/denied  |
| Event Response | <b>NVR:</b> record video; play beep sound; execute system command to activate other programs; e-mail notification<br><b>Device:</b> pop-up window with live video; switch to hotspot window; play beep sound; activate external device through digital output; upload snapshot to FTP server; execute system command to activate other programs; e-mail notification with snapshots; command a PTZ device to go to a preset point |
| Manual Event   | Manually activate external devices through digital output via live view monitor   |

## • System

|                             |  |
|-----------------------------|--|
| Operating System            | Win 7 (64 bit) Std. Embedded   |
| Permission Control          | Unlimited number of users, Active Directory, customizable permissions for user groups; playback password protected, password validity period |
| Language                    | Multi-language support   |
| Language Import / Export    | Possibility to import or export language packs for convenient local language management  |
| Customizable User Interface | Define the layout of user interface for live view and playback   |

## • Remote Access

|                       |  |
|-----------------------|--|
| PC Client Program     | User interface program (Workstation) with live view, PTZ, playback, e-Map, event management, setup   |
| PC Web Browser        | Microsoft Internet Explorer with live view, PTZ, playback, e-Map, event management, setup  |
| Mobile Client Program | Mobile device application (ACTI Mobile Client) supports live view, PTZ control, event or time based search and playback.<br>Supported devices: iPhone, iPad, iTouch and Android device |

## • Hardware

|                            |   |
|----------------------------|---|
| CPU                        | Intel Processor   |
| Local Display Interface    | DVI, VGA, Display Port  |
| Ethernet Ports             | LAN1: 10/100/1000 Mbps<br>LAN2: 10/100/1000 Mbps                |
| USB                        | 8 ( 2 Front Ports, 6 Rear Ports)                                |
| Dimensions (W x H x D)     | 88 x 482 x 560 mm (3.5" x 19" x 22.1")                          |
| Weight                     | 11.42 kg (25.17 lb)   |
| Operating Temperature      | 0°C ~ 40°C (32°F ~ 104°F)                                       |
| Operating Humidity         | 10%~85% RH  |
| Power Source / Consumption | 110V~220V AC 50/60Hz / 85W                                      |
| Approvals                  | CE (EN 55022 Class B, EN 55024), FCC (Part15 Subpart B Class B) |

## • Integration

|                        |   |
|------------------------|---|
| Unified Solution       | Fully compatible with ACTI cameras, encoders, NVR 3.0 |
| Open Platform Solution | Support ONVIF compliant devices                       |

\* All specifications are subject to change without notice.

\* All brand names and registered trademarks are the property of their respective owners.

www.acti.com

