

LBB 1957/00 Plena vészhangosítási billentyűzet

www.boschsecurity.hu



BOSCH

Életre tervezve



- ▶ Seven zone selection keys
- ▶ LED indications for zone selection
- ▶ Up to eight keypads can be connected together

The LBB 1957/00 Call Station Keypad is an extension to the LBB 1956/00 Plena vészhangosítási rendszer Call Station that adds seven additional zone-select keys. It has the same stable metal base as the call station. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops.

Főbb funkciók

Each call station supports six zone selections. Connecting one of these keypads, adds seven zones or zone groups that can be selected. Up to eight keypads can be added to an LBB 1956/00 call station. LEDs on the keypad indicate the active zones.

Controls and indicators

- Seven zone selection keys
- Seven zone selection LEDs
- Eight DIP switches

Interconnections

- Two RJ45 jacks
- 24 VDC input
- Keypad connector

Tanúsítványok és engedélyek

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1

Régió Tanúsítvány

Európa	CE
--------	----

Tartozékok

Quantity	Components
1	LBB 1957/00 Call Station Keypad

Műszaki specifikációk

Electrical

Power Supply	
Voltage range	24 VDC supplied by LBB 1956/00
Current consumption	< 15 mA

Mechanical

Base dimensions	40 x 100 x 235 mm (1.57 x 3.97 x 9.25 in)
Weight	Approx. 1 kg
Mounting	Bracket coupled with LBB 1956/00 or other LBB 1957/00
Color	Charcoal with silver

Environmental

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Rendelési információ

LBB 1957/00 Plena vészhangosítási billentyűzet

An extension to the LBB 1956/00 Plena vészhangosítási rendszer Call Station that adds seven additional zone-select keys.

Rendelési szám **LBB1957/00**

Képviselő:

Hungary:

Robert Bosch Kft.
Gyömrői út 120.
1103 Budapest
Phone: +36 1 4313 200
Fax: +36 1 4313 222
hu.securitysystems@bosch.com
www.boschsecurity.hu